


Restoring, Using the EntraPass Demo Backup

- 1- Install the Entrapass Edition – DEMO – found under the reference CD or downloaded from the website www.EntraPASS.com
- 2- Uncompressed the ENTRAPASS DEMO BACKUP downloaded from the website store the file on your hard drive.
- 3- Reboot the computer.
- 4- Connect your demo unit to your computer.
- 5- Execute the EntraPass DEMO Edition application. 
- 6- Login (user name and password is already typed).
- 7- Go under the BACKUP tab and click on RESTORE DATA. 
- 8- Locate the uncompressed folder stored under step # 2 and click on OK.
- 9- A message saying that the backup was restored successfully will appear.
- 10- Logout and log back in. 

- 11- Go under the DEVICES tab and click on CONTROLLER. 
- 12- Select the controller from the down arrow and then click on the KT-300 tab.



General KT-300 Options

Serial number 00000000

- 13- Locate the serial number of the controller and type it in under the field labeled SERIAL NUMBER (i.e.: A3011987). Click on Save. 
- 14- Go under the USERS tab and click on card. Select one card using the up arrow key right next to the card number (00:00001).



Card number 00:00001

- 15- Click on the SAVE AS  icon and enter a real card number from one of the card that were supplied with the demo unit. You may select DELETE THE ORIGINAL CARD and hit OK. Than hit SAVE. 
- 16- You may repeat step # 15 for all the cards you want to define. You may select another card (step 14) in order to get more than one profile.